Coaxial-to-Ethernet
Conversion Kit

KiweeBroadband

KB-M3-03
MoCA 2.5 Adapter

Model#KB-M3-03

User Guide

Table of Contents

1. Introduction 1
2. Package Contents 1
3. Requirements 1
4. Features 2
5. Setup Instructions 2
   - *Connecting the First Adapter* *2*
   - *Connecting Additional Adapters* *4*
6. MoCA protected Setup (MPS) 6
7. Web Management 6
8. Specifications 7
9. Safety and Compliance *7*
10. Warranty and Support *8*

1. Introduction

Thank you for purchasing the KB-M3-03 MoCA 2.5 Adapter. This device allows you to extend your home network using existing coaxial cabling. It provides high-speed Ethernet connectivity anywhere a coaxial outlet is available, ensuring a stable and reliable connection for streaming, gaming, and high-bandwidth applications. The built-in Ethernet port also supports PoE+ (Power over Ethernet Plus), allowing compatible devices to receive both power and data through a single Ethernet cable.

This guide provides step-by-step instructions for setup and troubleshooting.





2. Package Contents

- KB-M3-03 MoCA 2.5 Adapter
- Coaxial cable
- Power adapter
- Quick Start Guide
- Ethernet cable

3. Requirements

- An available coaxial port
- An electrical outlet near the installation location

4. Features

2.5G Ethernet Port: Provides ultra-fast data transfer speeds.
PoE+ Technology: Supplies data and power over a single Ethernet cable to compatible devices, simplifying installation.
MoCA 2.5 Technology: High-speed coaxial networking with up to 2.5 Gbps throughput.
TV Pass-through Port: Maintains TV/STB connectivity.
LED Indicators:

- **Power LED**: Solid green when powered on.
- **MoCA LED**: Solid green when a MoCA connection is established.
- **Ethernet LED**:
  - Green: 2500 Mbps link
  - Orange: 1000 Mbps link
  - Red: 10/100 Mbps link
  - Blinking: Data transmission in progress
- **PoE LED**: Solid green when a PoE connection is established

5. Setup Instruction

Connecting the First Adapter

1. **Disconnect** the coaxial cable from your TV or set-top box.
2. **Connect** that coaxial cable to the "TV" port on the MoCA adapter.



3. **Attach** a new coaxial cable from the wall outlet to the "DATA" port on the adapter.



4. **Connect** one end of an Ethernet cable to your modem/router.

5. **Plug** the other end into one of the Ethernet ports on the adapter.



6. If you connect a Power over Ethernet (PoE) device, the PoE LED indicator will turn green, signaling that the connection is successful and power is being supplied to the device.



7. **Power** on the adapter using the provided power adapter.

KB-M3-03 MoCA 2.5 Adapter





When complete, the setup should look similar to the figure below:



Your home network is now extended over the coaxial infrastructure.

Connecting Additional Adapters

1. **Find** a coaxial outlet near the desired location.
2. **Disconnect** any existing coaxial cable from a TV/STB (if applicable).
3. **Connect** that cable to the "TV" port on the adapter.
4. **Attach** a new coaxial cable from the wall outlet to the "DATA" port on the adapter.
5. **Use** an Ethernet cable to connect the adapter to your device (e.g., PC, gaming console, or access point).



6. If you connect a Power over Ethernet (PoE) device, the PoE LED indicator will turn green, signaling that the connection is successful and power is being supplied to the device.
7. **Plug in** the power adapter and turn on the unit.
8. **Make** sure the Power, Ethernet and MoCA lights are solid green.



Repeat these steps to add more adapters as needed.

6. MoCA protected Setup (MPS)

MPS simplifies the connection of MoCA devices using a shared password.

1. Press the **MPS button** on any existing MoCA device.
2. Within **2 minutes**, press the **MPS button** on the KB-M3-03 adapter.

The **MoCA LED** will blink and turn solid once successfully paired.

7. Web Management

Each adapter has a built-in web interface for advanced configuration.

- **Default IP Address**: 192.168.144.200
- **Login**: admin
- **Password**: maxlinear

To access:

1. Set your computer's IP to 192.168.144.x (where x is 1-254, except 200).
2. Connect your PC to the adapter via Ethernet.
3. Open a browser and enter http://192.168.144.200.
4. Adjust settings such as frequency range, transmission rate, and IP configuration.

8. Specifications

Model Number: KB-M3-03
Ethernet Ports: 1 x 2.5G LAN
MoCA 2.5 - DATA Port (Extended D-band: 1125MHz~1675MHz)
PoE Standard IEEE802.3af (15.4W)/IEEE802.3at (30W)
TV Port (**Frequency Range** - 5MHz~1002MHz)
LED Indicators: Power, MoCA, LAN, PoE
Power : 48VDC, 1A
Certifications : FCC, CE, IC

Environnemental

Ambient temperature - 0ºC to 40ºC (32ºF to 104ºF)
Storage temperature -- 20ºC to 85ºC (-4ºF to 185ºF)
Operating humidity - 10% to 85% non-condensing
Storage humidity - 5% to 90% non-condensing
Note: Specifications are subject to change without notice

9. Safety and Compliance

- Keep the device dry; do not expose it to water or high humidity.
- Do not block ventilation openings.
- Use only the provided power adapter.
- For coaxial cable installations, ensure proper grounding per ANSI/NFPA70 regulations.

Regulatory Compliance

FCC (USA)

This device complies with Part 15 of the FCC Rules. Operation is subject to the following conditions: (1) it may not cause harmful interference, and (2) it must accept any interference received.

CE (EU)

This product complies with EMC Directive 2014/30/EU and RoHS Directive 2011/65/EU, meeting:

- EN 55032: EMC – Emission requirements
- EN 55035: EMC – Immunity requirements

10. Warranty and Support

Warranty

- **Hardware**: 1-year limited warranty.
- **Software updates**: 120 days from the date of purchase.

Technical Support

For troubleshooting and assistance, contact: **info@kiwee-broadband.com**.

Common Issues & Solutions

MoCA LED is off:

- Ensure the adapter is correctly connected to the coaxial outlet.
- Try a different coaxial outlet.
- Verify that your home's coaxial network is connected properly.

Cable modem or set-top box stops working:

- Use a coaxial splitter instead of connecting directly.
- Install a MoCA POE (Point of Entry) filter.

Incompatible with DirecTV/DISH:

- These adapters work with cable or terrestrial TV; contact your provider for satellite-compatible solutions.

Factory Reset

To reset the device into factory default settings, press the reset button available under KB-M3-03 for 10 seconds.



For additional support, visit our website or email us at **info@kiwee-broadband.com**.

Thank you for choosing Kiwee Broadband. We hope you enjoy a seamless networking experience!